



The ultimate in clean power

A Group brand |  legrand

Give the
**NO.1 PROTECTION
TO YOUR PC**
with India's No.1 UPS company



NUMERIC
Digital 600 EX

Micro Processor Based Design - Fully micro processor based design ensures high reliability and accuracy.

Automatic Voltage Regulation - The Super boost AVR provides regulated clean power for a wide input voltage window of 140 to 300V AC, which allows the UPS to work in mains mode even under very low & high voltage conditions, thereby extending the life of the battery.

Full time EMI / RFI Suppression - Eliminates high frequency electrical noise that are harmful to the computer and the main cause for data corruption.

Cold Start Capability - Ability to start the UPS and perform file saving, document printing etc., when AC mains power supply is unavailable.

Overload - Safeguards the UPS and load against damage due to overload / short circuit.

Intelligent battery Management - Prevents the dissipation of battery energy by automatically shutting down the UPS when the load is very less or if there is no load to the UPS while operating in back-up mode.

www.numericups.com

Toll Free -1800 425 3266

NUMERIC

End to end power protection solutions.

Technical Specifications

Capacity	VA/W	600 VA
Input	Voltage	230V AC
	Voltage Range	140 - 300 VAC
	Frequency	50 Hz ± 6%
Output	Voltage (Batt. Mode)	230V AC ± 10%
	Frequency	50 Hz ± 1%
	Waveform	Quasi Sine Wave
Battery	Battery Type	Sealed Lead Acid Maintenance Free
	Battery Capacity, Nos.	12 V, 7AH, 1 No.
	Recharge Time	5 - 6 Hrs For 90% Charge
Backup Time	Single PC Load with 17" TFT / LCD Monitor	Upto 20 Minutes
Transfer Time	Typical	Less Than 4 Ms
Audible Alarm	Battery Discharge	Mains Fail, Battery Low, Overload
Physical	Dimension (H X W X D IN MM)	140 X 100 X 310
Weight	Net Weight	5.5 Kg
Protection	Full Protection	Under / Over Voltage, Spike / Surge Suppression, Overload, Short Circuit
Environment	Operating Environment	32°F - 104°F at full load, 0-90% relative humidity
	Noise Level	Non-condensing Less than 45db



Digital L1 Series
600VA - 2 KVA



Digital L1 SW Series
1KVA - 3 KVA



Digital Home Power
500VA - 2 KVA

*Back-up time may vary depending on the PC configuration.

NUMERIC GLOBAL NETWORK



NUMERIC HOUSE No.5 , Sir P.S.Sivasamy Salai, Mylapore, Chennai - 600 004, INDIA .
Tel : +91 -44-2499 3266 Fax : +91 -44-24998210 E-mail : info@numericups.com



A Group brand | Legrand

REGIONAL OFFICE: AHMEDABAD 079 - 27488779 / 556 **BANGALORE** 080 - 43038000, 01 / 02 / 03 / 04 **BHOPAL** 0755 - 2764201, 2764202
CHENNAI 044 - 24982502, 24982511, 24990466, 24990064, 24993266 **COCHIN** 0484 - 2324616, 2322334 **COIMBATORE** 0422 - 2242290, 2243716, 2243740 **HYDERABAD** 040-27603048, 27662817 **KOLKATA** 033 -24609233, 24609234, 24609032 **LUCKNOW** 0522 - 2206110, 2206112 **MADURAI** 0452-2604555, 2602629 **MUMBAI** 022-28373953/54/55 **NEW DELHI** 011-25571347/48/49



Toll Free No. 1 800 425 3266
www.numericups.com
NPDM/MKT/BRO/OLI/01

Please Refer our website : www.numericups.com for list of our service centers.